

DEWALT®

IF YOU HAVE ANY QUESTIONS OR COMMENTS ABOUT THIS OR ANY DEWALT TOOL, CALL US AT: 1800 654 155 (Aust) or 09 526 2556 (NZ).

The batteries in your new battery pack are not fully charged! First read the safety instructions, then follow charging notes and procedures.

SAFETY INSTRUCTIONS FOR POWER TOOLS

When using power tools, always observe the safety regulations applicable in your country to reduce the risk of fire, electric shock and personal injury. Read the following safety instructions before attempting to operate this product. Keep these instructions in a safe place.

General Safety Rules

WARNING! Read all instructions. Failure to follow all instructions listed below may result in electric shock, fire and/or serious injury. The term "power tool" in all of the warnings listed below refers to your mains operated (corded) power tool or battery operated (cordless) power tool.

SAVE THESE INSTRUCTIONS

Electrical Safety

The electric motor has been designed for one voltage only. Always check that the power supply corresponds to the voltage on the rating plate. 240 V AC means your tool will operate on alternating current. As little as 10% lower voltage can cause loss of power and can result in overheating. All DeWALT tools are factory tested; if this tool does not operate, check the power supply. Your DeWALT tool is double insulated, therefore no earth wire is required.

- **Young children and the infirm.** This appliance is not intended for use by young children or infirm persons without supervision. Young children should be supervised to ensure that they do not play with this appliance.
- **Replacement of the supply cord.** If the supply cord is damaged, it must be replaced by the manufacturer or an authorised DeWALT Service Centre in order to avoid a hazard.

READ ALL INSTRUCTIONS

- **Do not incinerate the battery pack even if it is severely damaged or is completely worn out.** The battery pack can explode in a fire.
- **A small leakage of liquid from the battery pack cells may occur under extreme usage or temperature conditions.** This does not indicate a failure. However, if the outer seal is broken and this leakage gets on your skin:
 - a. Wash quickly with soap and water.
 - b. Neutralize with a mild acid such as lemon juice or vinegar.
 - c. If battery liquid gets into your eyes, flush them with clean water for a minimum of 10 minutes and seek immediate medical attention. (**Medical Note:** The liquid is 25–35% solution of potassium hydroxide.)
- Charge the battery packs only in DeWALT chargers.
- **DO NOT** splash or immerse in water or other liquids.
- **Do not store or use the tool and battery pack in locations where the temperature may reach or exceed 105°F (40 °C) (such as outside sheds or metal buildings in summer).**
- **DO NOT** probe pack with conductive objects.
- Maintain clean and open vent holes.

NOTE: Review and observe all of the **Important Charging Notes** in the DeWALT charger instruction manual.

⚠ DANGER: Never attempt to open the battery pack for any reason. If battery pack case is cracked or damaged, do not insert into charger. Electric shock or electrocution may result. Damaged battery packs should be returned to service center for recycling.

⚠ CAUTION: Battery pack must be securely attached to tool. If battery pack is detached, personal injury may result.

NOTE: Battery storage and carrying caps are provided for use when- whenever the battery is out of the tool or charger. Remove cap before placing battery in charger or tool.

⚠ WARNING: Do not store or carry battery so that metal objects can contact exposed battery terminals. For example, do not place battery in aprons, pockets, tool boxes, product kit boxes, drawers, etc., with loose nails, screws, keys, etc. without battery cap. **Transporting batteries can possibly cause fires if the battery terminals inadvertently come in contact with conductive materials such as keys, coins, hand tools and the like.** The US Department of Transportation Hazardous Material Regulations (HMR) actually prohibit transporting batteries in commerce or on airplanes (i.e., packed in suitcases and carry-luggage) UNLESS they are properly protected from short circuits. So when



transporting individual batteries, make sure that the battery terminals are protected and well insulated from materials that could contact them and cause a short circuit.

The RBRC™ Seal

The RBRC™ (Rechargeable Battery Recycling Corporation) Seal on the nickel-cadmium battery (or battery pack) indicates that the costs to recycle the battery (or battery pack) at the end of its useful life have already been paid by DeWALT. In some areas, it is illegal to place spent nickel-cadmium batteries in the trash or municipal solid waste stream and the RBRC program provides an environmentally conscious alternative.



RBRC™ in cooperation with DeWALT and other battery users, has established programs in the United States to facilitate the collection of spent nickel-cadmium batteries. Help protect our environment and conserve natural resources by returning the spent nickel-cadmium battery to an authorized DeWALT service center or to your local retailer for recycling. You may also contact your local recycling center for information on where to drop off the spent battery.

RBRC™ is a registered trademark of the *Rechargeable Battery Recycling Corporation*.

GUARANTEE

Full One Year Warranty

DeWALT heavy duty industrial tools are warranted for one year from date of purchase. We will repair, without charge, any defects due to faulty materials or workmanship. Please return the complete unit, transportation prepaid, to any DeWALT Service Centre, or any authorised service station.

This warranty does not apply to:

- Accessories
- Damage caused where repairs have been made or attempted by others
- Damage due to misuse, neglect, wear and tear, alteration or modification.

30 DAY NO RISK SATISFACTION GUARANTEE

If you are dissatisfied with any DeWALT power tool, for any reason, simply return it to the point of purchase with your sales receipt within 30 days for a replacement unit or a full refund.

FREE WARNING LABEL REPLACEMENT: If your warning labels become illegible or are missing, call 1800-654-155 for a free replacement.

DeWALT Battery and Charger Systems

Battery	Output Nominal		Chargers/Charge Time																	
			240 Volts									12 Volts								
			97014	98014	DW9106	DW9107	DW9108	DW9115	DW9116	DW9117	DW9118	DE9116	DE9118	DW9111	DC011	DW0245	DE2046	DW9109		
Voltage	Amp Hour	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X			
DW0242	24	2.0	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X		
DE0240-XJ	24	2.0	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X		
DW0240	24	1.7	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X		
DW9096	18	2.4	X	X	X	X	X	60	X	60	X	60	X	60	X	X	X	60		
DE9095-XJ	18	2.0	X	X	X	X	X	X	X	60	X	60	X	60	X	X	X	60		
DE9091-XJ	14.4	2.0	45	45	45	45	45	45	15	45	15	90	45	45	45	X	X	45		
DW9091	14.4	1.7	45	45	45	45	45	45	15	45	15	90	45	45	45	X	X	45		
DC9071	12	2.4	60	60	60	60	60	60	15	60	15	60	60	60	60	X	X	60		
DE9074-XJ	12	1.25	45	45	45	45	45	30	15	30	15	60	30	30	30	X	X	30		
DW9072	12	1.2	45	45	45	45	45	30	15	30	12	60	30	30	30	X	X	30		
DE9071-XJ	12	2.0	60	60	60	60	60	45	15	45	15	90	45	45	45	X	X	45		
DW9071	12	1.7	60	60	60	60	40	X	X	X	X	X	X	X	X	X	X	X		
DW9050	12	1.3	40	40	40	40	40	X	15	15	X	X	X	X	X	X	X	X		
DW9063	9.6	1.25	45	45	45	45	45	30	15	30	15	60	30	30	30	X	X	30		
DW9062	9.6	1.3	45	45	45	45	30	30	15	30	12	60	30	30	30	X	X	30		
DW9061	9.6	1.7	60	60	60	60	45	45	15	45	15	90	45	45	45	X	X	45		
DW9048	9.6	1.3	40	40	40	40	X	X	15	X	X	X	X	X	X	X	X	X		
DW9057	7.2	1.25	45	45	45	45	30	30	15	30	12	60	30	30	30	X	X	30		
DW9046	7.2	1.3	40	40	40	40	X	X	15	X	X	X	X	X	X	X	X	X		
DC9096	18	2.4	X	X	X	X	X	60	X	60	20	X	X	60	60	X	X	60		
DC9091	14.4	2.4	60	60	60	60	60	60	15	60	15	60	60	60	60	X	X	60		

X Indicates that the battery pack is not compatible with that specific charger.

All charge times are approximate. Actual charge time may vary.

Read the instruction manual for more specific information.

The battery voltage is nominal, it can measure above or below depending on the state of charge.